

# SINGLE ZONE ALARM MODEL SZA210 AND SZA220



## FEATURES:

- Monitor Single Closed or Open Circuit with End of Line Resistor
- Simple Visual Display with Audible
  - Yellow LED = Disarmed
  - Green LED = Secure
  - Red LED = Alarm
- Key-Switch or Push-Button for Arm/Disarm/Reset

<u>SPECIFICATIONS</u>	
<b>MOUNTING</b>	Recessed and Surface Mount
<b>SIZE</b>	4 1/2" X 4 1/2" X 2 1/2"
<b>COLOR</b>	White Aluminum Faceplate Optional White Leviton Plastic Back Box
<b>POWER</b>	Requires 12 VDC Power Supply
<b>INPUTS</b>	Normally Closed or Open Circuit with End Of Line Resistor Arm/Disarm/Reset - Key-Switch or Push-Button
<b>OUTPUTS</b>	Yellow LED = Disarmed Green LED = Loop Status Secure Red LED = Alarm Audible - Low Level Piezo upon Alarm
<b>OTHER</b>	Call to request other options and features



MODEL SZA220 RECESSED  
SINGLE ZONE ALARM WITH  
KEY-SWITCH ARM/DISARM

**OPERATION:** Flair Single Zone Alarms are versatile, low cost alarms that can be used in a wide range of applications such as pool alarms, smokers doors, emergency exits and any other situation where the door needs to be monitored and a bypass capability is desired. The Door Alarm monitors a closed loop circuit and will alarm immediately upon door opening. The alarm can be bypassed with a key-switch or push-button. A SPDT Relay can be provided to follow the status of the door or alarm.